Data Sheet

TEV-Series - Valve Regulated Lead Acid Battery TEV12260

SPECIFICATIONS			
Nominal voltage	12	V	
20-hr rate Capacity to 10.5V at 20°C	26	Ah	
10-hr rate Capacity to 10.8V at 20°C	20	Ah	
	22.1	All	
DIMENSIONS	107 (14)		
Length	197 (±1)	mm	
Width	165 (±1)	mm	
Height	170 (±2) N/A	mm	
(height over terminals)		mm	
Mass (typical) TERMINAL TYPE	9.6	kg	
Female threaded terminal	M6	mm	
	7	Nm	
OPERATING TEMPERATURE RANGE			
Storage (in fully charged condition)		-20°C to +60°C	
Charge		o +50°C	
Discharge	-20°C to	o +60°C	
STORAGE			
Capacity loss per month at 20°C (approx)	3	%	
CASE MATERIAL			
Standard Option	ABS (UL.94:HB)		
Flame retardant option (FR)	ABS (U	ABS (UL94:V0)	
CHARGE VOLTAGE			
Float charge voltage at 20°C	13.65 (±1%) 2.275 (±1%)	V V/cell	
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C	
Cyclic (or Boost) charge at 20°C	14.5 (±3%) 2.42 (±3%)	V V/cell	
Cyclic Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C	
CHARGE CURRENT			
Float charge current limit	No limit	А	
Cyclic (or Boost) charge current limit	6.50	А	
MAXIMUM DISCHARGE CURRENT			
1 second	500	A	
1 minute	260	A	
CYCLIC LIFE DATA			
100% DOD down to 80% capacity	300	cycles	
75% DOD down to 80% capacity	500	cycles	
50% DOD down to 80% capacity	600	cycles	
	1400	cycles	
25% DOD down to 80% capacity IMPEDANCE	1400	Cycles	
Measured at 1 kHz	8.2	ml	
	0.2	ml	
PERFORMANCE & CHARACTERISTICS			
Refer to the technical manual	TEV		
DESIGN LIFE			
EUROBAT Classification: Standard Commercial	3 to 5	years	
SAFETY			



LAYOI	UT	
	Θ	\oplus

3RD PARTY CERTIFICATIONS

ISO 9001 - Quality Management Systems ISO 14001 - Environmental Management Systems EN 18001 - OHSAS Management Systems



UNDERWRITERS LABORATORIES Inc.

STANDARDS

IEC61056 IEC60895-21/22







Can be installed and operated in any orientation except permanently inverted

Handles

Installation

Batteries must not be suspended by their handles (where fitted)

Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

Gas Release

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed container

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations

ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.1 / Issue Date: July 2010

YUASA

www.yuasaeurope.com	TEV	