ENL-Series - Valve Regulated Lead Acid Battery ENL160-6

SPECIFICATIONS			
Nominal voltage	6	V	
10-hr rate Capacity to 5.4V at 20°C	163	Ah	
10-min rate Constant Power to 1.6V/cell at 20°C	638	Watts	
DIMENSIONS			
Length	305 (±1)	mm	
Width	210 (±1)	mm	
Height	240 (±1)	mm	
(height over terminals)	N/A	mm	
Mass (typical)	35.0	kg	
TERMINAL TYPE		Ŭ	
Threaded terminal - (M=Male or F=Female)	M8 (F)	mm	
Torque	6 (±0.5)	Nm	
OPERATING TEMPERATURE RANGE			
Storage (in fully charged condition)	-20°C to +50°C		
Charge		-15°C to +50°C	
Discharge	_	-20°C to +60°C	
STORAGE			
Capacity loss per month at 20°C (approx)	3	%	
CASE MATERIAL		,,,	
Flame retardant	ABS (III	L94:V0)	
CHARGE VOLTAGE	7.55 (525 1.75)		
	6.78 (±1%)	V	
Float charge voltage at 20°C	2.26 (±1%)	V/cell	
Float Charge voltage temperature correction factor (for variations from the standard 20°C)	-3	mV/cell/°C	
Boost charge at 20°C	7.2 (±2%) 2.40 (±2%)	V V/cell	
Boost Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C	
CHARGE CURRENT			
Float charge current limit	No limit	А	
Boost charge current limit	40.75	Α	
MAXIMUM DISCHARGE CURRENT			
1 second	1500	А	
1 minute	960	A	
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE		•	
(according to EN IEC 60896-21)			
Internal resistance	2.15	m	
Short-Circuit current	3200	Α	
IMPEDANCE	3200	, ,	
Measured at 1 kHz	1.7	m	
PERFORMANCE & CHARACTERISTICS	1		
Refer to the technical manual	ENL		
	ENL		
DESIGN LIFE			
EUROBAT Classification: High Performance	- 40:		
EUROBAT Classification: Long Life	12+	years	
Yuasa design life @ 20°C	15	years	
SAFETY			



SPECIFICATIONS

Can be installed and operated in any orientation except permanently inverted

Handles

Batteries must not be suspended by their handles (where fitted)

Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.


Gas Release

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed container

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations





3RD PARTY CERTIFICATIONS

ISO 9001 - Quality Management Systems
ISO 14001 - Environmental Management Systems
EN 18001 - OHSAS Management Systems
UNDERWRITERS LABORATORIES Inc.



STANDARDS

IEC61056 IEC60896-21/22







ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.2 / Issue Date: March 2011



YUASA BATTERY SALES UK LTD. Unit 13, Hunts Rise South Marston Industrial Estate SN3 4TG UK