DIGITRONY 230 START 230V 12-24V code 807575

Digital battery charger and starter with electronic control of the charging current, automatic interruption and restart (TRONIC). Normal (CHARGE), automatic (TRONIC), quick (BOOST) charge of all types of maintenance free, sealed batteries (GEL/AGM), free electrolyte batteries (WET) with 12/24V voltages and starting of cars, vans and light trucks. Characteristics: display to check charging current, voltage and battery charging level * choice of TEST, CHARGE, TRONIC mode * choice of outputvoltage, type of charge, charging mode * protection against overloads and polarity reversal.







Technical Data

Standards:	LVD: EN 60335-2-29	EMC: EN 55014-1,2;	EMC: EN 61000-3-2,3

CODE	V_{PH}	$P_{C/S}$	START	A_{EFF}	A_{EN}	A 1V/C	$A_{START\ MAX}$
	V50/60Hz	W	V	A	A	A	A
807575	230 1 ph	0,8 3,6	12 24	30	20	120	180

C MIN/MAX		W H L	kg	BAR CODE			
Ah15h		mm(L,W,H)	kg		pz/pallet	pz/pallet - B	
30 400	2	225 290 205	9,1	800489778284 3	56	42	