

DIGISTART 340 230V 12-24V code 829327

Digital battery charger and starter with electronic control of the charging current, automatic interruption and restart (PULSE-TRONIC) for charging all types of maintenance free, sealed batteries(GEL/AGM), free electrolyte batteries (WET) with 12/24V voltages and quick starting of cars, vans and light trucks. Characteristics: microprocessor control * display to check charging current, voltage and battery charging level * choice of TEST, CHARGE, TRONIC mode * CHARGE function: constant current charge as set on the front panel * choice of output voltage, type of charge, charging mode * protection against overloads and polarity reversal.



AUTOMOTIVE



Technical Data

Standards:	LVD: EN 60335-2-29	EMC: EN 55014-1,2;	EMC: EN 61000-3-2,3				
CODE	V _{PH}	P _{C/S}	START	A _{MIN} A _{MAX}	A _{EFF}	A _{EN}	A _{1V/C}
829327	V50/60Hz 230 1 ph	W 1 6,4	V 12 24	A 1 30	A 45	A 30	A 180
A _{START} A _{MAX}	C _{MIN/MAX}	W _H L	kg	BAR CODE			
A 300	Ah15h 10 450	mm(L,W,H) 305 360 630	kg 13,8	800489773281 7	pz/pallet 18		